

### Rescue 5000 Heavy-Duty Rescue 6000 Brute Power Extreme Duty

These products are designed to use two 12-V Group 31 AGM Sealed Lead Acid Batteries with 3/8" threaded posts rated 900 CCA or greater.



#### **WARNING: Risk of Acid Burns and Permanent Equipment Damage**

- Do not use flooded lead acid batteries.
- Battery acid can leak and cause injury
- Using flooded lead acid batteries voids all warranties.

Make sure the blue power selector plug on the front of the unit is disconnected.

Open the front cover of the battery compartment – remove the four screws. Inside you will see two battery compartments, one upper compartment in the back of the unit, and a lower compartment at the bottom in the front of the unit. A ratcheting battery hold-down strap is pre-installed. All of the wiring is labeled with numbers 1-4. Follow the directions below to connect the wires to the proper battery terminals in the correct order.




#### **WARNING: Risk of Electric Shock, Sparking, and Battery Explosion**


- Insure that all cables are connected to correct battery terminals (positive and negative)
- Do not allow unconnected cable ends to touch each other or any metal parts

#### **Follow These Wire Connection Instructions:**

1. Remove the cable tie securing the ratcheting battery hold-down strap, and feed the strap through the ratchet so it will fit around the two batteries when they are in position.
2. Connect the two wires labeled 2 to the negative post of the top shelf battery.
3. With the negative wires connected, fit the battery into the top shelf, negative terminals first. Make sure the ratcheting hold-down strap fits under and over the battery correctly, but leave it loose.
4. Fit the other battery into the bottom compartment, making sure that the ratcheting hold-down fits under and over the battery correctly. Tighten the hold-down to secure both batteries.
5. Connect the four wires labeled 4 to the negative post of the lower battery.
6. Connect the four wires labeled 1 to the positive post of upper battery.
7. Connect the two wires labeled 3 to the positive post of lower battery.



Top shelf battery.



Bottom compartment battery.

To replace or service batteries, be sure to reverse this sequence exactly.

Save the positive cable terminal protectors and cover the positive terminals whenever they are disconnected from batteries. Reinstall the front compartment cover with the four retaining screws.

**Register your product at [www.quickcable.com/register](http://www.quickcable.com/register)**