

QUICK[®] DC/AC Power Inverter

1000 Watt Modified Sine Wave

Specifications

Part Number	303206
Output Power Continuous	1000W
Output Power Surge	3000W, 20ms
AC Output Voltage	115V
Regulation	±10%
Output Wave Form	Modified Sine Wave
DC Input Voltage	10V – 15V
Low Battery Alarm	DC 10.5V ±0.5V
Low Battery Shut Down	DC 9.5V ±0.5V
Frequency	60 ±2Hz
Efficiency (Full Load)	90%
No Load Current Draw	<0.6A
Over Temperature Protection	60° ±5°
Overload Protection	Yes
Input Short Circuit Protection	Yes
AC Output Socket	North American 3-Pin Type
Dimensions	15-1/2" x 9-1/2" x 3-1/2"
Net Weight	1.6 KGS

3700 Quick Drive • Franksville, WI 53126
Phone 1-800-558-8667 • Fax 1-800-733-8611
sales@quickcable.com • quickcable.com

6395 Kestrel Road • Mississauga, ON L5T 1Z5
Phone 1-800-728-1742 • Fax 1-905-362-1614
cdnsales@quickcable.com • quickcable.com